


PCB MOUNTING HOLES
(VIEWED FROM COPPER SIDE)



CIRCUIT DIAGRAM

Dimensions unless otherwise specified	
Size Range	Tolerance
$L \leq 1$	± 0.15
$1 < L \leq 8$	± 0.20
$8 < L \leq 23$	± 0.25
$23 < L \leq 50$	± 0.30
ANGAL	$\pm 1^\circ$

NO.	PART NAME	Q'TY	MATERIAL (THICKNESS, COLOR)	REMARK
11	SEPARATOR	2	POM	RoHS COMPLIANT
10	MAKE TERMINAL (1a, 5e)	2	QSn6.5-0.1Y t=0.3 (C5210R-H)	Ag-PLATED, RoHS COMPLIANT
9	WASHER	1	PBT G10	RoHS COMPLIANT
8	TIP TERMINAL (4d)	1	QSn6.5-0.1Y t=0.4 (C5210R-H)	Ag-PLATED RoHS COMPLIANT
7	BREAK TERMINAL (3c, 7g)	2	H62Y t=0.4 (C2680R-H)	
6	TRANSFER TERMINAL (2b, 6f)	2	QSn6.5-0.1Y t=0.35 (C5210R-H)	Ag-PLATED RoHS COMPLIANT
5	RING TERMINAL (8h)	1	QSn6.5-0.1Y t=0.3 (C5210R-H)	
4	EARTH TERMINAL (9d)	1	Fe t=0.6 (STEEL)	CuSn-PLATED; RoHS COMPLIANT
3	HOUSING	1	PBT G10	RoHS COMPLIANT
2	PLASTIC SCREW	1	PBT G10	RoHS COMPLIANT
1	BUSHING	1	H59 (COPPER ALLOY)	Ni-PLATED; RoHS COMPLIANT

	SCALE: 1:1	NAME: PHONE JACK
	VIEW:	CAT. NO. SCJ-0640-X-1
	UNIT: mm	